
# SPLIT CURRENT TRANSFORMERS SPECIFICATION SHEET - CTSS (80 x 160)









:	=	П		E e		E 3
		I		E		E 3
	• ◎	_	М		<ul><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li></li><li><!--</th--><th>III III</th></li></ul>	III III
Outline Size			Wind	ow Size	Insta	llation Size
L	W	Н	a	е	M	N
185	53	248	80	160	118	45

### Electrical Diagram

#### Parameters



Part No.	Ratio(A)	Accuracy	Burden (VA)	Frequency	Insulation Strength	
	1000/5	1. 0	≤10			
	1500/5	1. 0	≤15	50/60Hz	≪3KV	
	2000/5	0. 5	≤15			
80X160	2500/5	0.5	≤15			
	3000/5	0. 5	≤15			
	4000/5	0. 5	≤15			
	5000/5	0. 5	≤15			

## Performance Curve

## Specification



The split core series current transformer has been specially designed to facilitate their installation in new or already existing net works. They may be installed without opening any cable or bus-bar circuit.

The connection of conventional CTs usually requires the interruption of the primary side circuit to pass cables or bur-bars through the transformer core or to connect such cables to the prima ry terminals. This series transformers core may be easily opened and they may be installed and connected without any supply interruption. Thus saving time and the installation costs.



Unit 1 Salisbury House, Salisbury Road,

Newton Abbot, TQ12 2DF

**T:** 01626 368 595

E: sales@pjwmeters.com

W: pjwmeters.com